
# WESTERBEKE D-NETT DIESEL GENERATOR

# Fully networked to NMEA 2000®





7.6/5.7 EDTA Marine Diesel Generator (shown with optional white paint)

# The First Electronic Diesel Generators NMEA 2000® Certified

Westerbeke D-NET™ electronic generators are equipped with standard NMEA 2000® compliant databus communication. NMEA 2000® is a network for shipboard communications developed under National Marine Electronics Association (NMEA) standards. NMEA 2000® generators, combined with other certified components, allow boat builders and their customers to significantly reduce the cost, weight and space normally required to run cables throughout the vessel. All certified components freely communicate and are linked to just one NMEA 2000® cable using "T" connections that simplify networking.

#### Information At Your Fingertips

All Westerbeke D-NET™ generators have available digital controls offering simplified and easy to understand information on operational status and, if necessary, system diagnostics. Westerbeke also features "at a glance" illuminated lights indicating proper operation. They monitor battery voltage, generator voltage, generator frequency, oil pressure, coolant and exhaust temperature. All this information may be viewed from a distance—all green lights indicate referenced systems are functioning properly. Further details are available on the screen display. The user may conveniently scroll for operational or diagnostic information without encountering "codes". Westerbeke uses text so the user does not have to refer to a manual to decipher numeric information.

## **Quiet, Slow-Speed Digital Operation**

Operating at 1800 or 1500-rpm with a tuned air intake silencer and 3-cylinder engine, this D-NET™ generator runs smooth and quiet. Augmenting this desired effect is the electronic governing that virtually eliminates "droop" when load is applied. Include the optional Sound Guard SST with high quality stainless steel base and frame with stylish powder coated aluminum panels and you have a generator as attractive as it is quiet.



7.6/5.7 EDTA Marine Diesel Generator (shown with optional white paint)

#### Standard Features

- NMEA 2000® compliant databus communication
- Digital display and diagnostics panel
- Electronic governing
- Safety shut-downs: overspeed, underspeed, low oil pressure, high exhaust and high coolant temperature
- AC circuit breaker
- 50 amp battery charging alternator
- Power take-off interface
- Self-bleeding fuel system
- Fresh water cooling and coolant recovery tank
- 45 degree water injected exhaust elbow
- Gear driven raw water pump
- Tuned air intake silencer
- Anti-vibration mounts fail safe rubber type
- Lube oil drain hose and drip trav
- Oil fill top and side
- Belt guard
- Operators' Manual and parts list
- 5-year limited warranty
- Meets CARB & U.S. EPA regulations

### Digital Display









#### **Generator Design**

**DESIGN:** Brushless, four pole, revolving, power take-off. **VOLTAGE REGULATION:** Standard +/- 5% no load to full load. FREQUENCY REGULATION: .5 Hz (.60%) no load to full load. INSULATION: Class "H", as defined by NEMA MG1-1.65.

TEMPERATURE RISE: Within NEMA MG1-22.40 definition when operating at full load.

**COOLING:** Cast centrifugal blower, direct connected.

**ELECTROMAGNETIC INTERFERENCE LEVEL:** Exceeds requirements

for most marine radio-telephones and standard TVs.

	Electrical Characteristics					Ratings		Engine	
Model	Volts	Amps	Hertz	Phase	Wire	Power Factor	KW	RPM	Start
7.6 EDTA-614	120/240	63.3/31.6	60	1	4	1.0	7.6	1800	Remote
5.7 EDTA-514	230	24.7	50	1	4	1.0	5.7	1500	Remote

SpecificationsNumber of cylinders3 Cylinder vertical in-lineType4 cycleDisplacement58.09 cu. in. (.952 liter)Bore and stroke2.99" x 2.76" (75.9 mm x 70.0 mm)Compression ratio23:1Rated rpm @ 60/50 Hz1800/1500HP @ 1800 rpm12.4Maximum angle of continuous operationNot to exceed 25° in all directionsExhaust elbow connection2" OD (50.8mm)Raw water connection1" OD (25.4mm)Dry weight407 lbs. (185 kilos)Combustion systemSwirl typeAspirationNaturally aspiratedLubrication systemForced lubrication by gear pumpCooling system4 quarts (3.78 liters)Starting aid12 volt sheathed type glow plugFuel consumption (approx.)1800 rpm1500 rpm100% load GPH (LPH)0.93 (3.5)0.69 (2.6)75% load GPH (LPH)0.93 (3.5)0.53 (2.0)50% load GPH (LPH)0.50 (1.9)0.39 (1.5)25% load GPH (LPH)0.36 (1.4)0.28 (1.1)Fuel injection pumpBosch type, with solenoid shutoffGovernorElectronicInjectorsThrottle typeFuel FilterSecondary, replaceable type	Chacifications			
Type 4 cycle Displacement 58.09 cu. in. (.952 liter) Bore and stroke 2.99" x 2.76" (75.9 mm x 70.0 mm) Compression ratio 23:1 Rated rpm @ 60/50 Hz 1800/1500 HP @ 1800 rpm 12.4 Maximum angle of continuous operation Not to exceed 25° in all directions Exhaust elbow connection 2" OD (50.8mm) Raw water connection 1" OD (25.4mm) Dry weight 407 lbs. (185 kilos) Combustion system Swirl type Aspiration Naturally aspirated Lubrication system Forced lubrication by gear pump Cooling system 4 quarts (3.78 liters) Starting aid 12 volt sheathed type glow plug Fuel consumption (approx.) 1800 rpm 1500 rpm 100% load GPH (LPH) 0.93 (3.5) 0.69 (2.6) 75% load GPH (LPH) 0.67 (2.5) 0.53 (2.0) 50% load GPH (LPH) 0.36 (1.4) 0.28 (1.1) Fuel injection pump Bosch type, with solenoid shutoff Governor Electronic Injectors	Number of cylinders	3 Cylinder vertical in-line		
Displacement 58.09 cu. in. (.952 liter)  Bore and stroke 2.99" x 2.76" (75.9 mm x 70.0 mm)  Compression ratio 23:1  Rated rpm @ 60/50 Hz 1800/1500  HP @ 1800 rpm 12.4  Maximum angle of continuous operation Not to exceed 25° in all directions  Exhaust elbow connection 2" OD (50.8mm)  Raw water connection 1" OD (25.4mm)  Dry weight 407 lbs. (185 kilos)  Combustion system Swirl type  Aspiration Naturally aspirated  Lubrication system Forced lubrication by gear pump  Cooling system 4 quarts (3.78 liters)  Starting aid 12 volt sheathed type glow plug  Fuel consumption (approx.) 1800 rpm 1500 rpm  100% load GPH (LPH) 0.93 (3.5) 0.69 (2.6)  75% load GPH (LPH) 0.67 (2.5) 0.53 (2.0)  50% load GPH (LPH) 0.36 (1.4) 0.28 (1.1)  Fuel injection pump Bosch type, with solenoid shutoff Governor Electronic  Injectors Throttle type	,	•		
Compression ratio  Rated rpm @ 60/50 Hz  HP @ 1800 rpm  12.4  Maximum angle of continuous operation  Exhaust elbow connection  Raw water connection  Dry weight  Combustion system  Aspiration  Lubrication system  Cooling system  Starting aid  Fuel consumption (approx.)  1800 rpm  1800 rpm  1900 (25.4mm)  Naturally aspirated  Lubrication by gear pump  Cooling system  4 quarts (3.78 liters)  Starting aid  12 volt sheathed type glow plug  Fuel consumption (approx.)  1800 rpm  1500 rpm  100% load GPH (LPH)  0.93 (3.5)  0.69 (2.6)  75% load GPH (LPH)  0.50 (1.9)  0.39 (1.5)  25% load GPH (LPH)  0.36 (1.4)  0.28 (1.1)  Fuel injection pump  Bosch type, with solenoid shutoff  Governor  Electronic  Injectors		,		
Compression ratio  Rated rpm @ 60/50 Hz  HP @ 1800 rpm  12.4  Maximum angle of continuous operation  Exhaust elbow connection  Raw water connection  Dry weight  Combustion system  Aspiration  Lubrication system  Cooling system  Starting aid  Fuel consumption (approx.)  1800 rpm  1800 rpm  1900 (25.4mm)  Naturally aspirated  Lubrication by gear pump  Cooling system  4 quarts (3.78 liters)  Starting aid  12 volt sheathed type glow plug  Fuel consumption (approx.)  1800 rpm  1500 rpm  100% load GPH (LPH)  0.93 (3.5)  0.69 (2.6)  75% load GPH (LPH)  0.50 (1.9)  0.39 (1.5)  25% load GPH (LPH)  0.36 (1.4)  0.28 (1.1)  Fuel injection pump  Bosch type, with solenoid shutoff  Governor  Electronic  Injectors	Bore and stroke	,		
HP @ 1800 rpm 12.4  Maximum angle of continuous operation Not to exceed 25° in all directions Exhaust elbow connection 2" OD (50.8mm)  Raw water connection 1" OD (25.4mm)  Dry weight 407 lbs. (185 kilos)  Combustion system Swirl type  Aspiration Naturally aspirated  Lubrication system Forced lubrication by gear pump  Cooling system 4 quarts (3.78 liters)  Starting aid 12 volt sheathed type glow plug  Fuel consumption (approx.) 1800 rpm 1500 rpm  100% load GPH (LPH) 0.93 (3.5) 0.69 (2.6)  75% load GPH (LPH) 0.67 (2.5) 0.53 (2.0)  50% load GPH (LPH) 0.50 (1.9) 0.39 (1.5)  25% load GPH (LPH) 0.36 (1.4) 0.28 (1.1)  Fuel injection pump Bosch type, with solenoid shutoff Governor Electronic  Injectors Throttle type	Compression ratio			
Maximum angle of continuous operation  Exhaust elbow connection  Raw water connection  Dry weight  Combustion system  Aspiration  Lubrication system  Cooling system  Starting aid  Fuel consumption (approx.)  1800 rpm  1800 rpm  1500 rpm  100% load GPH (LPH)  0.93 (3.5)  0.69 (2.6)  75% load GPH (LPH)  0.50 (1.9)  0.39 (1.1)  Fuel injection pump  Governor  Injectors  Not to exceed 25° in all directions  2" OD (50.8mm)  Not to exceed 25° in all directions  2" OD (50.8mm)  100 (25.4mm)  100 (26.4mm)  100	Rated rpm @ 60/50 Hz	1800/1500		
Exhaust elbow connection 2" OD (50.8mm)  Raw water connection 1" OD (25.4mm)  Dry weight 407 lbs. (185 kilos)  Combustion system Swirl type  Aspiration Naturally aspirated  Lubrication system Forced lubrication by gear pump  Cooling system 4 quarts (3.78 liters)  Starting aid 12 volt sheathed type glow plug  Fuel consumption (approx.) 1800 rpm 1500 rpm  100% load GPH (LPH) 0.93 (3.5) 0.69 (2.6)  75% load GPH (LPH) 0.67 (2.5) 0.53 (2.0)  50% load GPH (LPH) 0.50 (1.9) 0.39 (1.5)  25% load GPH (LPH) 0.36 (1.4) 0.28 (1.1)  Fuel injection pump Bosch type, with solenoid shutoff Governor Electronic  Injectors Throttle type	HP @ 1800 rpm	12.4		
Raw water connection Dry weight Combustion system Aspiration Cooling system Starting aid Fuel consumption (approx.) 1800 rpm 100% load GPH (LPH) 25% load GPH (LPH) 25% load GPH (LPH) 30.36 (1.4) 50% load GPH (LPH) 50% load	Maximum angle of continuous operation	Not to exceed 25° in all directions		
Dry weight 407 lbs. (185 kilos)  Combustion system Swirl type Aspiration Naturally aspirated Lubrication system Forced lubrication by gear pump Cooling system 4 quarts (3.78 liters)  Starting aid 12 volt sheathed type glow plug Fuel consumption (approx.) 1800 rpm 1500 rpm 100% load GPH (LPH) 0.93 (3.5) 0.69 (2.6) 75% load GPH (LPH) 0.67 (2.5) 0.53 (2.0) 50% load GPH (LPH) 0.50 (1.9) 0.39 (1.5) 25% load GPH (LPH) 0.36 (1.4) 0.28 (1.1) Fuel injection pump Bosch type, with solenoid shutoff Governor Electronic Injectors Throttle type	Exhaust elbow connection			
Combustion system  Aspiration  Lubrication system  Cooling system  Starting aid  Fuel consumption (approx.)  100% load GPH (LPH)  50% load GPH (LPH)  25% load GPH (LPH)  Fuel injection pump  Governor  Injectors  Swirl type  Naturally aspirated  Lubrication by gear pump  4 quarts (3.78 liters)  12 volt sheathed type glow plug  12 volt sheathed type glow plug  1500 rpm  1500 rpm  1500 rpm  1500 rpm  1500 rpm  10.93 (3.5)  0.69 (2.6)  75% load GPH (LPH)  0.67 (2.5)  0.53 (2.0)  0.39 (1.5)  25% load GPH (LPH)  0.36 (1.4)  0.28 (1.1)  Fuel injectors  Throttle type	Raw water connection	,		
Aspiration Lubrication system Cooling system Starting aid Fuel consumption (approx.) 100% load GPH (LPH) 150% load GPH (LPH) 1	Dry weight	407 lbs. (185 kilos)		
Lubrication system  Cooling system  4 quarts (3.78 liters)  Starting aid  12 volt sheathed type glow plug  Fuel consumption (approx.)  1800 rpm  1500 rpm  100% load GPH (LPH)  0.93 (3.5)  0.69 (2.6)  75% load GPH (LPH)  0.67 (2.5)  0.53 (2.0)  50% load GPH (LPH)  0.50 (1.9)  0.39 (1.5)  25% load GPH (LPH)  0.36 (1.4)  0.28 (1.1)  Fuel injection pump  Governor  Electronic  Injectors  Throttle type	Combustion system	Swirl type		
Cooling system         4 quarts (3.78 liters)           Starting aid         12 volt sheathed type glow plug           Fuel consumption (approx.)         1800 rpm         1500 rpm           100% load GPH (LPH)         0.93 (3.5)         0.69 (2.6)           75% load GPH (LPH)         0.67 (2.5)         0.53 (2.0)           50% load GPH (LPH)         0.50 (1.9)         0.39 (1.5)           25% load GPH (LPH)         0.36 (1.4)         0.28 (1.1)           Fuel injection pump         Bosch type, with solenoid shutoff           Governor         Electronic           Injectors         Throttle type	Aspiration	Naturally aspirated		
Starting aid         12 volt sheathed type glow plug           Fuel consumption (approx.)         1800 rpm         1500 rpm           100% load GPH (LPH)         0.93 (3.5)         0.69 (2.6)           75% load GPH (LPH)         0.67 (2.5)         0.53 (2.0)           50% load GPH (LPH)         0.50 (1.9)         0.39 (1.5)           25% load GPH (LPH)         0.36 (1.4)         0.28 (1.1)           Fuel injection pump         Bosch type, with solenoid shutoff           Governor         Electronic           Injectors         Throttle type	Lubrication system	Forced lubrication by gear pump		
Fuel consumption (approx.)         1800 rpm         1500 rpm           100% load GPH (LPH)         0.93 (3.5)         0.69 (2.6)           75% load GPH (LPH)         0.67 (2.5)         0.53 (2.0)           50% load GPH (LPH)         0.50 (1.9)         0.39 (1.5)           25% load GPH (LPH)         0.36 (1.4)         0.28 (1.1)           Fuel injection pump         Bosch type, with solenoid shutoff           Governor         Electronic           Injectors         Throttle type	Cooling system	4 quarts (3.78 liters)		
100% load GPH (LPH)       0.93 (3.5)       0.69 (2.6)         75% load GPH (LPH)       0.67 (2.5)       0.53 (2.0)         50% load GPH (LPH)       0.50 (1.9)       0.39 (1.5)         25% load GPH (LPH)       0.36 (1.4)       0.28 (1.1)         Fuel injection pump       Bosch type, with solenoid shutoff         Governor       Electronic         Injectors       Throttle type	Starting aid	12 volt sheathed type glow plug		
75% load GPH (LPH)         0.67 (2.5)         0.53 (2.0)           50% load GPH (LPH)         0.50 (1.9)         0.39 (1.5)           25% load GPH (LPH)         0.36 (1.4)         0.28 (1.1)           Fuel injection pump         Bosch type, with solenoid shutoff           Governor         Electronic           Injectors         Throttle type	Fuel consumption (approx.)	1800 rpm 1500 rpm		
50% load GPH (LPH) 0.50 (1.9) 0.39 (1.5) 25% load GPH (LPH) 0.36 (1.4) 0.28 (1.1) Fuel injection pump Bosch type, with solenoid shutoff Governor Electronic Injectors Throttle type	100% load GPH (LPH)	0.93 (3.5) 0.69 (2.6)		
25% load GPH (LPH)  Fuel injection pump  Governor  Injectors  0.36 (1.4)  Bosch type, with solenoid shutoff  Electronic  Throttle type	75% load GPH (LPH)	0.67 (2.5) 0.53 (2.0)		
Fuel injection pump  Governor  Injectors  Bosch type, with solenoid shutoff Electronic Throttle type	50% load GPH (LPH)	0.50 (1.9) 0.39 (1.5)		
Governor Electronic Injectors Throttle type	25% load GPH (LPH)	0.36 (1.4) 0.28 (1.1)		
Injectors Throttle type	Fuel injection pump	Bosch type, with solenoid shutoff		
2	Governor	Electronic		
Fuel Filter Secondary, replaceable type	Injectors	Throttle type		
, p	Fuel Filter	Secondary, replaceable type		
Fuel transfer pump 12 volt electric type	Fuel transfer pump	12 volt electric type		

Fuel supply and return piping	1/4" ID (6.35 mm) minimum
	3/8" ID (9.53 mm) maximum
	,
Lube oil filter	Full flow, spin-on element
Lubricant capacity	3.8 quarts (3.6 liters)
Starting motor	12 volt, solenoid, actuated shift
Alternator	50 amps
7 intorriator	oo ampo
Cold cranking amps	190
	10 yelta DC magatiya arayad
Electrical system	12 volts DC, negative ground

Construction	n – Engine Components
Cylinder head	Cast Iron
Cylinder block	Cast Iron
Crankshaft	Forged crankshaft, four main bearings
Valves	Overhead valves, rotating type
Fuel System	Self-bleeding
Intake system	Tuned intake silencer
	for maximum noise reduction
Cooling system	Fresh water-cooled with heat exchanger
Exhaust manifold	Cast aluminum, fresh water-cooled

Optional Equipment
Remote digital display and start/stop
Sound Guard SST
Hydro-hush muffler and fittings; fuel water separator
Anti-siphon valve with 1" inch stainless steel loop
Ship-to-shore switch; power take-off adapter
"A" on board spare parts kit
"B" extended cruising spare parts kit
Generator set available painted white upon request (standard red)

